## **Single Phase Hybrid Storage Inverter**

## 4-6 kW Plus Series



The Afore AF low voltage series storage Inverters are designed to increase energy independence for homeowners. The power range is from 4kW to 6kW, compatible with low voltage (40-60V) batteries.

Energy management is based on time-of-use and demand charge rate structures, which significantly reduce the amount of energy purchased from the public grid.

Thanks for the UPS function (switch time < 10ms), that enables the crucial loads power on during outages. Additionally, under the backup operation mode, the inverter provides you up to 150% peak output overloading.

The AF low voltage series storage inverters are integrated with Arc Fault Circuit Interrupter (AFCI) and rapid shutdown.



MAX. 120A Max. Charge/ Discharge Current 120A



**PV OVERSIZE** 1.5 Times PV Oversize



MPPT CHANNELS
Up to 2 MPPT Channels



UPS FUNCTION Switch Time < 10ms



PARALLEL
Max.6 Parallel Stacking

Support for Time-of-use Optimization



Build in Anti-feed-in Function

Configurable Operation Modes



- ☐- Compact Size and Easy Installation

Arc Fault Circuit Interrupter (AFCI) (Optional)



Smart Monitoring & Remote Firmware Upgrade

The charging and discharging power of the battery is greater



Off-grid mode, with a larger load capacity, the maximum load can be 6KVA

Technical Data	AF4K-SLP	AF4.6K-SLP	AF5K-SLP	AF5.5K-SLP	AF6K-SLP
PV Input					
Max. Input Power (kW)	6	6.9	7.5	8.3	9
Max. PV Voltage (V)			550		
MPPT Range (V)	120 500	120 500	80 - 500	160 500	470 500
Full MPPT Range (V)	120 - 500	130 - 500	150 - 500	160 - 500	170 - 500
Normal Voltage (V) Startup Voltage (V)			360 100		
Max. Input Current (A)			18.5 x 2		
Max. Short Current (A)			26 x 2		
No. of MPP Tracker / No. of PV String			2/2		
Battery Port			- / -		
Max. Charge/Discharge Power (kW)	4.0	4.6	5.0	5.5	6.0
Max. Charge/Discharge Current (A)			120		
Battery Normal Voltage (V)			51.2		
Battery Voltage Range (V)			40 - 60		
Battery Type			Li-ion / Lead-acid etc.		
AC Grid					
Max Continuous Current (A)	19.0	22.0	23.0	26.0	28.0
Max Continuous Power (kVA)	4.0	4.6	5.0	5.5	6.0
Nominal Grid Current (A)	18.2 / 17.4	21.0 / 20.0	22.8 / 21.8	25.0 / 24.0	27.3 / 26.1
Nominal Grid Voltage (V)	198 to 242 @ 220 / 207 to 253 @ 230				
Nominal Grid Frequency (Hz)			50 / 60		
Power Factor		0.999 (Adjustable f	rom 0.8 overexcited to	0.8 underexcited)	
Current THD (%)			< 3		
AC Load Output					
Max Continuous Current (A)	19.0	22.0	23.0	26.0	28.0
Max Continuous Power (kVA)	4.0	4.6	5.0	5.5	6.0
Max Peak Current (A) (10min)	27.3 / 26.1	31.4 / 30	34.1 / 32.7	37.8 / 36.1	41.0 / 39.2
Max Peak Power (kVA) (10min)	6.0	6.9	7.5	8.3	9.0
Nominal AC Voltage L-N (V)			220 / 230		
Nominal AC Frequency (Hz)			50 / 60		
Switching Time (ms)			Seamless < 3		
Voltage THD (%)  Efficiency			<u> </u>		
CEC Efficiency (%)			97.0		
Max. Efficiency (%)			97.6		
PV to Bat. Efficiency (%)			98.1		
Bat. between AC Efficiency (%)			96.8		
Protection			30.0		
PV Reverse Polarity Protection			Yes		
Over Current/Voltage Protection			Yes		
Anti-Islanding Protection			Yes		
AC Short Circuit Protection			Yes		
Residual Current Detection			Yes		
Ground Fault Monitoring			Yes		
Insulation Resister Detection			Yes		
PV Arc Detection			Yes		
Enclosure Protect Level			IP65 / NEMA4X		
AC/DC surge protection			Type II		
General Data			270 - 525 - 422		
Dimensions (W x H x D, mm)			370 x 535 x 192		
Weight (kg)			20.5		
Topology Cooling			Transformerless		
Relative Humidity			0 - 100 %		
Operating Temperature Range (°C)			- 25 to 60		
Operating Altitude (m)			< 4000		
Noise Emission (dB)			< 25		
Standby Consumption (W)			< 10		
Mounting			Wall Bracket		
Communication with RSD			SUNSPEC		
Display & Communication Interfaces		LCD, LED	), RS485, CAN, Wi-Fi, G	PRS, 4G	
· · · · · · · · · · · · · · · · · · ·		,	AS4777.2, VDE-AR-N410	•	